

HEX DIGITS 1ST → 2ND ↓	4-	5-	6-	7-	8-	9-	A-	B-	C-	D-	E-	F-
<b>-0</b>	(SP) SP010000	& SM030000	- SP100000	∨ SD210000	∪ SD230000	◦ SM190000	ą LA430000	• SD290000	{ SM110000	}	\ SM140000	0 ND100000
<b>-1</b>	(RSP) SP300000	é LE110000	/ SP120000	É LE120000	a LA010000	j LJ010000	~ SD190000	Ą LA440000	A LA020000	J LJ020000	÷ SA060000	1 ND010000
<b>-2</b>	â LA150000	ę LE430000	Â LA160000	Ę LE440000	b LB010000	k LK010000	s LS010000	ż LZ290000	B LB020000	K LK020000	S LS020000	2 ND020000
<b>-3</b>	ä LA170000	ë LE170000	Ä LA180000	Ë LE180000	c LC010000	l LL010000	t LT010000	Ť LT420000	C LC020000	L LL020000	T LT020000	3 ND030000
<b>-4</b>	‡ LT410000	ű LU270000	” SD250000	Û LU280000	d LD010000	m LM010000	u LU010000	Ż LZ300000	D LD020000	M LM020000	U LU020000	4 ND040000
<b>-5</b>	á LA110000	í LI110000	Á LA120000	Í LI120000	e LE010000	n LN010000	v LV010000	ş SM240000	E LE020000	N LN020000	V LV020000	5 ND050000
<b>-6</b>	ǎ LA230000	î LI150000	Ă LA240000	Î LI160000	f LF010000	o LO010000	w LW010000	ž LZ210000	F LF020000	O LO020000	W LW020000	6 ND060000
<b>-7</b>	č LC210000	ĭ LL210000	Č LC220000	Ľ LL220000	g LG010000	p LP010000	x LX010000	ź LZ110000	G LG020000	P LP020000	X LX020000	7 ND070000
<b>-8</b>	ç LC410000	í LL110000	Ç LC420000	Ĺ LL120000	h LH010000	q LQ010000	y LY010000	Ž LZ220000	H LH020000	Q LQ020000	Y LY020000	8 ND080000
<b>-9</b>	é LC110000	β LS610000	Ć LC120000	` SD130000	i LI010000	r LR010000	z LZ010000	Ż LZ120000	I LI020000	R LR020000	Z LZ020000	9 ND090000
<b>-A</b>	[ SM060000	] SM080000	 SM130000	: SP130000	ś LS110000	ł LL610000	Ś LS120000	Ł LL620000	(S̄H̄Y) SP320000	Ě LE220000	ǎ LD210000	Ď LD220000
<b>-B</b>	• SP110000	\$ SC030000	, SP080000	# SM010000	ň LN210000	ń LN110000	Ń LN220000	Ň LN120000	ô LO150000	ű LU250000	Ô LO160000	Ů LU260000
<b>-C</b>	< SA030000	* SM040000	% SM020000	@ SM050000	đ LD610000	š LS210000	Đ LD620000	Š LS220000	ö LO170000	ü LU170000	Ö LO180000	Ü LU180000
<b>-D</b>	( SP060000	) SP070000	_ SP090000	' SP050000	ý LY110000	• SD410000	Ý LY120000	” SD170000	ř LR110000	ť LT210000	Ř LR120000	Ť LT220000
<b>-E</b>	+ SA010000	; SP140000	> SA050000	= SA040000	ř LR210000	• SD430000	Ř LR220000	' SD110000	ó LO110000	ú LU110000	Ó LO120000	Ú LU120000
<b>-F</b>	! SP020000	^ SD150000	? SP150000	" SP040000	ş LS410000	⊗ SC010000	Ş LS420000	× SA070000	ő LO250000	ě LE210000	Ő LO260000	(EO)